



## Welcome to use SNPR122 IR sensor!

SNPR122 is a Short Distance IR Sensor. Its ON or OFF is controlled by hand movements. When you move your hands towards the IR sensor, it gets detection and turn on the light. The light will be switched off until the IR sensor detects another movement by hands.

## Product parameter

### Specifications:

Power source: 110-240V/AC

Rated Load: Max.500W (220-240V/AC)(incandescent lamp)

Power Frequency: 50/60Hz

200W (220-240V/AC)(energy-saving lamp)

Rated Current: 5A

Detection Distance: 5-6cm

Working Temperature: -20~+50°C

## Lifetime and warranty

Lifetime (hr)	26000-45000 at least
Warranty	1 year

## Use manual

### INSTALLATION :

- Ø Switch off the power.
- Ø Install the product on the wall with two enclosed inflated screws.
- Ø Connecting the power and the load to sensor as the connection-wire diagram.
- Ø Switch on the power and test it.

